


# MINI LED WALLPACK MINILWPP INSTALLATION INSTRUCTIONS



## WARNING

Please read instructions carefully before attempting to install fixture and retain instructions for future reference.

Caution: To avoid electrical shock hazard.

- Turn off the electricity before installing or servicing this fixture.
- Electrical connections need to comply with National Electric Code and Local Electric Code.
- The fixture should be installed by a qualified electrician.
- Do not touch the yellow portion of the LED array. Damage may occur.
- Do not wire fixture until fixture is mounted.
- Use wire rated for at least 80°C.

## APPLICATION/USE

This product is rated for use in wet locations and designed for surface mounting only. It is best to mount the fixture to a standard 4" electrical box. If a different size electrical box already exists to the mounting location, you may need to purchase additional equipment for installation.

## INSTALLATION

1. Loosen screws securing lens/fixture cover and remove.
2. Loosen reflector screw and remove reflector.
3. Knock out appropriate holes on back plate for mounting on wall over electrical box. For surface entrance, knock out the hole over conduit entrance on the bottom of fixture.
4. Remove paper backing from gasket and adhere over opening on back of housing
5. Caulk between fixture back and mounting surface to prevent water ingress. A high-grade caulking compound, such as silicon rubber, should be used.
6. Securely attach the fixture to the conduit or to the junction box. Secure fixture to mounting surface with appropriate hardware.
7. See "Fixture Wiring"
8. Re-install reflector and lens cover. Tighten screws which were loosened in Steps 1 and 2.

## FIXTURE WIRING

1. Connect the black fixture lead to the voltage supply lead with wire connector.
2. Connect the white fixture lead to the neutral supply lead with the wire connector.
3. Connect the green or green/yellow or bare copper ground lead to the supply ground lead with the wire connector.
4. Cap and insulate all unused leads.

Need help? Call 1-800.956.3456 to speak with our installation and product experts.